

| Furnace model | Electrical connection   | Amps | Connecting plug   |
|---------------|-------------------------|------|---|
| Top 16/R      | 2,6kW 230V 1/N/PE       | 11.3 | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| Top45eco      | 2,9 kW 230V 1/N/PE      | 12.6 | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| Top 45        | 3,6kW 230V 1/N/PE       | 15.7 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| Top 45/R      | 5,5kW 400V 3/N/PE       | 13.8 | 5-pin CEE plug, 16 Ampere   |
| Top60Leco     | 2,9kW 230V 1/N/PE       | 12.6 | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| Top 60        | 3,6kW 230V 1/N/PE       | 15.6 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| Top 60eco     | 3,6kW 230V 1/N/PE       | 15.6 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| Top 60/R      | 5,5kW 400V 2/N/PE       | 13.8 | 5-pin CEE plug, 16 Ampere   |
| Top 80        | 5,5 kW 230 V 1/N/PE     | 23.9 | 3-pin CEE plug, 32 Ampere   |
| Top 80        | 5,5kW 400V 3/N/PE       | 13.8 | 5-pin CEE plug, 16 Ampere   |
| Top100LE      | 6,0kW 400 V 2/N/PE      | 15   | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| Top 100       | 7,0 kW 230V 1/N/PE      | 30.4 | 3-pin CEE plug, 32 Ampere   |
| Top 100       | 7,0kW 400V 3/N/PE       | 10.1 | 5-pin CEE plug, 16 Ampere   |
| Top 130       | 9,0 kW 230V 1/N/PE      | 39.1 | Delivery at a fixed connection*   |
| Top 130       | 9,0kW 400V 3/N/PE       | 13   | 5-pin CEE plug, 16 Ampere   |
| Top140LE      | 6,0kW 230 V 1/N/PE      | 26.1 | 3-pin CEE plug, 32 Ampere   |
| Top 140       | 9,0 kW 230V 1/N/PE      | 39.1 | Delivery at a fixed connection*   |
| Top 140       | 9,0kW 400V 3/N/PE       | 13   | 5-pin CEE plug, 16 Ampere   |
| Top 160       | 9,0 kW 230V 1/N/PE      | 39.1 | Delivery at a fixed connection*   |
| Top 160       | 9,0kW 400V 3/N/PE       | 13   | 5-pin CEE plug, 16 Ampere   |
| Top190        | 11,0 kW 230 V 1/N/PE    | 47.8 | Delivery at a fixed connection*   |
| Top 190       | 11,0kW 400V 3/N/PE      | 15.9 | 5-pin CEE plug, 16 Ampere   |
| Top 220       | 15,0kW 400V 3/N/PE      | 21.7 | 5-pin CEE plug, 32 Ampere   |
| HO 70/L       | 3,6 kW 230 V 1/N/PE     | 15.7 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| HO 70/R       | 5,5 kW 400 V 2/N/PE     | 13.8 | 5-pin CEE plug, 16 Ampere   |
| HO 100        | 5,5 kW 400 V 2/N/PE     | 13.8 | 5-pin CEE plug, 16 Ampere   |
| N 40E         | 2,9kW 230V 1/N/PE       | 12.6 | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| N 40/ER       | 5,5kW 400V 3/N/PE       | 13.8 | 5-pin CEE plug, 16 Ampere   |
| N 70 LE       | 2,9kW 230V 1/N/PE       | 12.6 | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| N 70E         | 3,6kW 230V 1/N/PE       | 15.7 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| N 70/ER       | 5,5kW 400V 2/N/PE       | 13.8 | 5-pin CEE plug, 16 Ampere   |
| N 100E        | 7,0 kW 230V 1/N/PE      | 30.4 | 3-pin CEE plug, 32 Ampere   |
| N 100E        | 7,0kW 400V 3/N/PE       | 10.1 | 5-pin CEE plug, 16 Ampere   |
| N 140LE       | 5,8 kW 230V 1/N/PE      | 25.2 | 3-pin CEE plug, 32 Ampere   |
| N 140E        | 9,0kW 400V 3/N/PE       | 13   | 5-pin CEE plug, 16 Ampere   |
| N 210LE       | 9,0 kW 230V 1/N/PE      | 39.1 | Delivery at a fixed connection*   |
| N210 E        | 11,0 kW 230 V 1/N/PE    | 47.8 | Delivery at a fixed connection*   |
| N 210E        | 11,0kW 400V 3/N/PE      | 15.9 | 5-pin CEE plug, 16 Ampere   |
| N 280LE       | 6,0 kW 230V 1/N/PE      | 26.1 | 3-pin CEE plug, 32 Ampere   |
| N 280E        | 15,0kW 400V 3/N/PE      | 21.7 | 5-pin CEE plug, 32 Ampere   |
| N 100         | 9,0 kW 230V 1/N/PE      | 39.1 | Delivery at a fixed connection*   |
| N 100         | 9,0kW 400 V 3/N/PE      | 13   | 5-pin CEE plug, 16 Ampere   |
| N150          | 11,0kW 230 V 3/PE       | 27.6 | 5-pin CEE plug, 32 Ampere   |
| N 150         | 11,0kW 400V 3/N/PE      | 15.9 | 5-pin CEE plug, 16 Ampere   |
| N 200         | 15,0kW 400V 3/N/PE      | 21.7 | 5-pin CEE plug, 32 Ampere   |
| N 300         | 20,0kW 400V 3/N/PE      | 28.9 | 5-pin CEE plug, 32 Ampere   |
| N 440         | 30,0kW 400V 3/N/PE      | 43.4 | Delivery at a fixed connection*   |
| N 660         | 40,0kW 400V 3/N/PE      | 57.8 | Delivery at a fixed connection *  |
| N 100/H       | 11,0kW 400V 3/N/PE      | 15.9 | 5-pin CEE plug, 16 Ampere   |
| N 150/H       | 15,0kW 400V 3/N/PE      | 21.7 | 5-pin CEE plug, 32 Ampere   |
| NW 150        | 11,0kW 400V 3/N/PE      | 15.9 | 5-pin CEE plug, 16 Ampere   |
| NW 300        | 20,0kW 400V 3/N/PE      | 28.9 | 5-pin CEE plug, 32 Ampere   |
| NW 440        | 30,0kW 400V 3/N/PE      | 43.7 | Delivery at a fixed connection*   |
| NW 660        | 40,4kW 400V 3/N/PE      | 59   | Delivery at a fixed connection*   |
| NW 1000       | 57,4kW 400V 3/N/PE      | 83.5 | Delivery at a fixed connection*   |
| GF 75         | 3,6kW 230V 1/N/PE       | 15.6 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| GF 75/R       | 5,5kW 400V 3/N/PE       | 13.8 | 5-pin CEE plug, 16 Ampere   |
| GF190LE       | 6,0kW 230V 1/N/PE       | 26.1 | 3-pin CEE plug, 32 Ampere   |
| GF 190        | 6,4kW 400V 2/N/PE       | 16   | 5-pin CEE plug, 16 Ampere   |
| GF 240        | 11,0kW 400V 3/N/PE      | 15.9 | 5-pin CEE plug, 16 Ampere   |
| GF 380        | 15,0kW 400V 3/N/PE      | 21.7 | 5-pin CEE plug, 32 Ampere   |
| F 30          | 2,0kW 230V 1/N/PE       | 8.7  | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| F 75L         | 3,6kW 230V 1/N/PE       | 15.7 | Socket outlet with earthing contact <b>(UK= Power cable with plug CEE 148,230V/16A)</b> |
| F 75          | 5,5kW 400V 2/N/PE       | 7.9  | 5-pin CEE plug, 16 Ampere   |
| F110 LE       | 6,0 kW 230V 1/N/PE      | 26.1 | 3-pin CEE plug, 32 Ampere   |
| F 110         | 7,5 kW 400 V 3/N/PE     | 10.8 | 5-pin CEE plug, 16 Ampere   |
| F 220         | 15,0 kW 400 V 3/N/PE    | 21.6 | 5-pin CEE plug, 32 Ampere   |
| MF 5          | 1,6 kW 230V / 1/N/PE    | 6.9  | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| LE1/11        | 1,5 kW 220-240 V 1/N/PE | 6.5  | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| LE 2/11       | 1,8 kW 230 V 1/N/PE     | 7.8  | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| LE 6/11       | 1,8 kW 230 V 1/N/PE     | 7.8  | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| LE14/11       | 2,9 kW 230V 1/N/PE      | 12.6 | <b>with UK-plug/</b> Socket outlet with earthing contact                                |
| GFM 420       | 18 kW 400 V 3/N/PE      | 26   | 5-pin CEE plug, 32 Ampere   |